



## ESL emulator for RENAULT cars



Old type ESL

ELV connector:

1- minus (-)

2- plus (+)

3- can high (H)

6- can low (L)

Jumper on emulator:  
SHORTED

New type ESL:

ELV connector:

1- minus (-)

2- plus (+)

3- can high (H)

6- can low (L)

4- connect to pin2 through 100ohm resistor

Jumper on emulator:

OPEN for 500kB CAN (late ones),  
SHORTED for 250kB CAN systems

Status LEDs:

GREEN: "locked", YELLOW: "unlocked"

